

Product Features

- 1, This product is a kind of energy-saving portable installation of solar energy products
- 2, It is widely used in gardens, streets, corridors, indoor and outdoor lighting
- 3, Easy to install: fixed and fixed installation, do not need any wiring and other complex installation process
- 4, The product is equipped with a USB charging port, which can be charged by solar energy and can be charged by the market.
- 5, Energy saving, there are 3 kinds of lighting modes, users can set up according to needs.
- 6, The product is equipped with remote control function, and the brightness can be adjusted to a large tune.

Specification

- 1, Solar panels: 6V1.5W
- 2, Battery: 18650 lithium battery 3.7V3000mAh
- 3, LED : 2835SMD 55pcs
- 4, Rated power: 6W
- 5, Flux: 800LM
- 6, Motion sensing range: 120°5-10M
- 7, Remote control distance: 5-10M

Working Modes:

- 1, Press Mode button for 3 seconds , light blinks 3 times, auto lights up in dim mode from dusk to dawn and turns into full brightness when motion detected within 5 -8 meters.10s after the automatic switch to weak light (no light at night, 10%, some people all bright)
- 2, Press Mode button again, light blinks 3 times, auto lights up in full brightness when motion detected within 5-8 meters, auto turns off when no motion detected.the lights will automatically open, about 10s after the lights will automatically turn off
- 3, Press Mode button again, light blinks 3 times , auto lights up in 1/2 brightness from dusk to dawn. (automatic night lights, the brightness is 50%)
- 4 , Press mode button again shut down (into hibernation), if you want to start the long press the button 3 seconds to boot, and then cycle 1,2,3 ,4 working modes.

Introduction to Remote Control Function:

- 1, ON is the power-on key, and the default mode 1 is after power - on
2. Press MODE1 for human body induction + slight brightness.
3. Press MODE2 for human body induction
4. Press MODE3 to make it always bright
- 5, No matter in any mode. Press the add and subtract button to adjust the brightness of the light.
6. OFF is the shutdown key. In any mode, press the OFF key to turn off the machine.
7. After the remote control is turned off, the key mode is also turned off synchronously.

USB charging port is used for auxiliary charging:

When the sun is not enough, you can use commercial power to charge, and the common Android data cable port is plugged into the USB port of the lamp body
When charging starts, the red light will come on.