

三折触控键盘

说明书

注意：正确操作本产品，请仔细阅读用户手册。

正面

背面

支持系统

Win/iOS/Android

●蓝牙对码连接：

1、请打开位于键盘侧边电源开关，蓝色灯亮起，按一下蓝牙对码开关，蓝灯闪烁进入对码模式。

2、打开“蓝牙”进入搜索模式。

3、直到发现“Bluetooth 3.0 Keyboard”然后点击下一步。

4、根据蓝牙提示，在键盘上输入对应的密码，按Enter键确定。

5、提示连接配对成功，您可以舒适地使用您的键盘了。

注：配对成功以后下次使用只需要打开蓝牙键盘电源及使用设备的蓝牙，蓝牙键盘将会自动搜索连接上次使用过的设备，不需要再进行配对操作。

产品功能

IOS/Android		Windows	
Fn+	对应功能	Fn+Shift	对应功能
	返回桌面		主页
	搜索		搜索
	全选		全选
	复制		复制
	粘贴		粘贴
	剪切		剪切
	上一曲		上一曲
	暂停/播放		暂停/播放
	下一曲		下一曲
	静音		静音
	音量减小		音量减小
	音量增大		音量增大
	锁屏		锁屏

技术规格

键盘尺寸：304.5X97.95X8mm(打开)
触控板尺寸：54.8X44.8mm
键盘重量：197.3g
工作距离：<15m
锂电池容量：140mAh
工作电压：3.7V

使用触控板工作电流：<8.63mA
使用按键工作电流：<3mA
待机电流：0.25mA
休眠电流：60μA
休眠时间：10分钟
唤醒方式：按任意键

触控板功能说明

单指点击 – 鼠标左键

双指点击 – 鼠标右键

双指上下滑动 – 垂直滚动

双指缩放

三指点击 – Win+组合键 (打开Cortana)

三指向左/向右滑动 – 活动窗口切换

三指向上扫 – Win+Tab组合键 (打开任务视图窗口)

三指向下扫 – Win+D组合键 (显示桌面)

注：该设备在iOS系统下触控板无功能

状态显示LED

•对码：打开电源开关，蓝牙指示灯蓝灯亮起，按下对码键，蓝灯闪烁

•充电：指示灯红色，充满灯灭；

•低电压指示：当电压低于3.3V，红色指示灯闪烁

提示：为了延长电池寿命，请您在不使用键盘时，关闭键盘的电源开关。

键盘保养

1、请勿将设备暴露于液体和潮湿的环境中或使其淋雨，请勿在浴缸、水槽、桑拿房、游泳池或蒸汽房附近使用。

2、请勿将设备暴露于过高或过低的温度下。

3、请勿长时间放置在阳光直射的地方。

4、请勿靠近明火，如烹饪用炉、蜡烛或者壁炉。

5、避免使用锋利器物刮擦产品，及时给产品进行充电以保证正常使用。

常见问题解答

1、平板无法连接蓝牙键盘？

1) 请先检查蓝牙键盘是否有进入配对状态。然后再打开平板电脑蓝牙搜索设备进行连接。

2) 检查蓝牙键盘电量是否充足，电量不足也会导致无法连接，请将蓝牙键盘充电后再使用。

2、键盘指示灯在使用途中一直闪烁？

键盘指示灯在使用途中一直闪烁，表示电池即将没电，请尽快将键盘充电。

3、设备显示蓝牙键盘断开连接？

蓝牙键盘在一段时间内不使用，设备为了省电将自动关闭蓝牙功能，按键盘任意键唤醒，蓝牙连接自动恢复。

Three Layer Folding Touchpad Keyboard

User’ s Manual

Note: Please read the user manual carefully before you start using this product

Front

Back

Compatible System

Win /iOS /Android

●Bluetooth pairing connection

1.Please turn on the power at the side of the keyboard, blue lights up, press the Bluetooth connection button, blue light will twinkle and into the match mode quickly.

2.Open the tablet PC setting “Bluetooth” into searching and pairing state.

3.You will find the “Bluetooth 3.0 Keyboard” and click to next step .

4.According to the table PC tips to input the correct password then click “Enter” button.

5.There have a tip for connecting successfully,you can use your keyboard comfortably .

Remarks：After connecting successfully the next time you don't need match code, just open the Bluetooth keyboard power switch and the tablet PC “Bluetooth” The BT keyboard will search the device and automatic connects.

Product features

IOS/Android		Windows	
Fn+	Corresponding function	Fn+Shift	Corresponding function
	Return to Desk		Home
	Search		Search
	Select		Select
	Copy		Copy
	Stick		Stick
	Cut		Cut
	Pre-Track		Pre-Track
	Play/Pause		Play/Pause
	Next		Next
	Mute		Mute
	Volume-		Volume-
	Volume+		Volume+
	Lock		Lock

Technical Specifications

Keyboard size：304.5X97.95X8mm(Open)
Touchpad size：54.8X44.8mm
Weight：197.3g
Working distance：<15m
Lithium battery capacity：140mAh
Working voltage：3.7V

Use touchpad the working current：<8.63mA
Use key the working current：<3mA
Standby current：0.25mA
Sleep current：60μA
Sleep time：Ten minutes
Awaken way：Arbitrarily key to awaken

Touchpad Functions

One finger click –left mouse

Two finger click –right mouse

Two finger slide – mouse wheel

Two finger stretch – Zoom

Three finger click– win+s combination key (Open the Cortana)

Three finger slid/right slid the left- Active window switch

Three finger slid up – win + Tab combination key (Open the browser window)

Three finger slid down -Win+D combination key(return back to Windows start menu)

Note: no touchpad function for the device under the IOS system

Status Display LED

• Connect：Open the power switch, blue lights up, press the connect button, blue light twinkles.

• Charging：Indicator light will be on red, after fully charging, the light crush out.

• Low Voltage Indication：When the voltage is below 3.3 V, red light twinkles.

Remarks: In order to prolong the life span of the battery, when you do not use the keyboard for a long time, please switch off the power.

Troubleshooting

Please contact the after-sales service.

Copyright

It is forbidden to reproduce any part of this quick start guide without the permission of seller.

Safety instructions

Do not open or repair this device, Do not use the device in a damp environment. Clean the device with a dry cloth.

FAQ

1.The tablet PC can't connect the BT keyboard？

1) At first check the BT keyboard is into match code state, then open the table PC Bluetooth searching.

2) Checking the BT keyboard Battery is enough, the battery low is also lead to can't connect, you need charge.

2.The keyboard indication light always flashing when use?

Keyboard indication always flashing when use, is means the battery will be no power，please charge the power as soon as possible.

3.The table PC display BT keyboard is disconnect?

The BT keyboard will into dormant to save the battery after some time later no use; press any key the BT keyboard will be awoken and working.

中文

成品尺寸：71x105mm
材质：100g双胶纸

背面